

7-32V Click the self-locking module

Model: DC 7-32V P1
Model: DC 7-32V P1 RF



Parameters:

Input voltage: DC 7-32V/Usb5V
Max.Current:2200W/10A
Wi-Fi Standard:Wi-Fi 2.4ghz b/g/n
Working temperature: -20°C~70°C
Size: 69*41*20mm


Checklist before using the device

- Your smart phone or tablet has connected to a 2.4g WiFi with internet.
- You have the correct WiFi PWD.



- You smart phone or tablet must have access to APP store,Google play.
- Your router is MAC-open.

User Guide

- 1 Start with "EWelink" APP.



- 2 Register an EWelink account.
- 3 If you have EWelink account,just login.
- 4 Power up.



- 5 On the device, the default call is closed and can be set to call or maintain in the APP change.

Add device flow to mobile APP

- 1 Press and hold the Match button for about 7 seconds until the WiFi red LED blinks fast (blinking twice and on) .

- 2 Tap on Ewelink app.

- 3 Select Quick Pairing.


special cases You can try compatibility Model (AP)



- 4 Input your WiFi password.



- 5 Name your device.



- 6 When the WiFi LED is on,the device is online.

- 7 Click the on/off buttons on the APP can control device,Manual control switch also can be display real-time on the APP.

Inching /Self-locking Switch

- 1、Click switch name.



- 2、Click ... , enter settings.



- 3、Click "Inching Settings" .



- 4、Turn on "Inching",set inching duration and save.



Remote control matches the code

Matching:

- 1 hold 433 matched button for 3 seconds,the blue LED light.
- 2 then long press the remote control buttons .
- 3 loosen the remote control buttons,matching success.




Clear code:

Long press the 433 pairing button for 15 seconds (RF working indicator is always on), loosen the 433 matching button,and the RF working indicator flashes rapidly for 5 times.
* note: the matching/clear code method is only available with RF function switch/module reference.

TROUBLESHOOTING

Solutions for the failure of product matching and offline:

Enter the homepage of App,click the icon in the lower right corner of the interface to enter.
"Message" >"hits" Guide" . "Profile" >"hits" Ewelink support"



If none of the above is resolved,please open it with another phone.Personal hotspot,try to read.