

Smart Plug User Manual	WiFi Smart Converter User Manual Product Schematic Function Key and Indicator Description 1.USBC1 2. USB A 3. LED indicator light. When the blue LED light flashes quickly, it means that the WiFi hotspot has been turned on. When the LED is on, it means that the socket	and USB output are turned on. When the LED goes out, it means that the socket and USB output are off. 4.button, Turn on/off if pressing 1 second. - Open WiFi hot spot if pressing 5seconds. 5.USBC2 Connect with "Smart Life" Use your phone to scan the QR code below or search "smart life" in application market to download and install the App	Step 1: Registration and login "smart life" APP. If you don't have the account of "Smart life" APP,register an account or sign in with cellphone number +verification code.This page describes the Registration process. 1. Tap "Register" from the interface; 2. It automatically pop-ups the window of "Privacy Policy", after you read completely and press "Agree" button; 3. The system will automatically determine your country/region. You can also select your country code by yourself. Enter the mobile No. or Email , and press the button of "Obtain verification code"; 4. Enter verification code and set the password;	5. Press the button of "Completed" to finish the registration, then for start to create the family. Make sure your phone is connected to WiFi in your home. Click "+" in the upper right corner of the homepage and select "Electrical outlet" from the device type.	Step 2: Connect with the power supply, long press the power button more than 5 seconds until the blue indicator enters into the fast flash mode. Select and press the button of "confirm indicator rapidly blink". Step 3: Enter your WiFi password for your phone and click "Confirm" to enter the page of the search device.
--	--	---	--	--	---

Step 4: Enter the device page, then complete the configuration	Take use of Statistic Function: Click the icon of "statistics" at the lower right corner ,it will enter the interface of "Electrical Quality Management". Check the current detailed data.	How to use Amazon Echo to control your Smart devices and Google Home?	FAQ About WiFi Connection: 1. How to Connect WiFi of Smart Device with the Mobile? This device can only support 2.4G but not 5G, so please confirm the mobile and WiFi router under 2.4G. If there is both 2.4G & 5G in router, you can access the setting of router to shut off 5G network firstly. (1). Please keep the devices & mobile close to the WiFi router as possible, because the signal of 2.4G is easily to be interfered; (2). Also, if the set channel of router is same with others, in this case, it looks strong signal	but in fact it will bring the false signal; You can switch the transmission channel from 1~11; (3). Another factor is that the terminal devices connected with the router reach maximum. 2. How to Enter AP Mode of Smart Socket? Long press 8s to blink rapidly, then continue to long press 8s to enter slow blink mode for AP connection. 3. If it's still unresolved, what am I Supposed to do? If it's still unresolved from the above FAQ, please try to share the WiFi Hot Spot from one mobile to another, and also connect the device through this WiFi Hot Spot, if it can be	connected, it proves that the smart devices run well but might the problem from router. Otherwise, it's the problem from the product. • Input Voltage: AC 110~240V 50/60Hz 16A • Output AC Socket: 10A□13A□16A□ MAX • PD Change Output: - Type-C1/Type-C2: 5V/9V/12V/15V=3A; 20V=3.25A 65W MaX - USB-A: 5V/9V=3A; 12V=2.5A 30W MaX - Type-C1+USB-C2: 45W+20W - Type-C1+USB-A: 45W+18W - Type-C1+Type-C2+USB-A: 45W+15W - Type-C2+USB-A: 15W
---	---	--	--	---	--