

产品参数表 Product Specification

SwitchMan R5
场景遥控器/Scene Controller



基本信息 Basic Information

产品系列 Product series	SwitchMan
产品类型 Type	随意贴开关(遥控器) Stick-on switch (remote controller)
供电 Power supply	6V(3V纽扣电池 x 2) 6V (3V button cell x 2)
电池型号 Battery model	CR2032
操控距离 Control distance	最大90米 (空旷区域) Max. 90m (Open space)
按键数量 Numbers of button	6
MCU	AK803
产品认证 Certification	CE/FCC/UKCA/SRRC/RoHS

外观信息 Appearance

产品颜色 Color	羌色 Dim Gray
产品规格 Product size	86x86x13.5mm
包装规格 Package size	97x89x17mm
产品净重 Net weight	91g
总重量 Total weight	111g
外壳材质 Casing material	PC V0

功能特性 Features

产品特点 Functions	R5是一款6键场景遥控器, 配合带有“轻智能网关”功能的设备一起使用, R5被网关添加成功后, 通过在eWeLink App场景中设置联动触发其他智能设备。 R5 is a 6-key scene remote controller and can work with the devices with “eWeLink-Remote” feature. When R5 is added into the gateway successfully, it can trigger other smart devices by setting Scene on eWeLink App.
-------------------	--

无线标准 Wireless Standard

无线协议 Wireless protocol	轻智能 eWeLink-Remote
天线 Antenna	内置板载天线 PCB board with antenna

使用环境 Working Enviroment

适用场所 Applicable place	室内使用 Indoor
工作温度 Working temperature	0°C ~ 40°C
工作湿度 Working humidity	5%-95% RH, 无冷凝 5%-95% RH, non-condensing
工作海拔 Working height	2000米以下 Less than 2000m

安装信息 Installation

安装方法 Installation methods	1. 磁吸 (取下后盖, 即可吸附在金属材质表面) 2. 3M胶黏贴 3. 通过螺丝安装在86型暗盒上 1. Magnetic attraction (remove the back cover, then it can be attached to the metal surface) 2. Pasted with 3M adhesive 3. Mounted on the 86 socket box with screws
------------------------------	--